

Royston Route Tables

This table shows all the routes that can be set from all signals on the Royston Sim.

In cases where more than one route is available to the same location, all are listed, with the 'preferred' route (the one that the interlocking will try first) shown at the top.

Only controlled signals are shown, and if the route can be autaset (using the 'a' button), this will be shown in the Notes column.

From	To	Points Normal	Points Reverse	Notes
CA103	C105	(none)	(none)	auto working, one-touch route
CA104	K986	(none)	(none)	auto working, one-touch route
K245	K253	2370	2369 2371	
	K981	2370 2371 2375 2376	2369	
	K983	2369 2375 2372		
K244	LK246	2369 2370	2371	no route from LK246
	K976	2370	2369 2371	
	SHERRIF'S	2370 2371	(none)	
K246	LK246	2369 2370 2371	(none)	no route from LK246
	K976	2370 2371	2369	
	SHERRIF'S	2371	2370	
K247	K983	2375	2372	
K249	K253	2370 2371	(none)	
	K981	2371 2375 2377	2370	call-on allowed
	K983	2371	2370 2375	call-on allowed
K253	K981	(none)	2376	call-on allowed
K975	K977	2369 2370 2371	(none)	auto working
	C103	2369 2370 2371 2375 2376 2377 2378	(none)	long route
K977	K253	2369 2370	2371	released from red
	K981	2369 2370 2371 2375 2376	(none)	call-on allowed
	K983	2369 2370 2371	2375	released from red, call-on allowed
K978	K244	(none)	2376	released from red
	K246	2375 2376	(none)	released from red
	K976	2370 2371 2375 2376	2369	
K980	K246	(none)	2375	released from red
	K976	2369 2372 2375	(none)	
	UP SIDING	2375	2372	released from red

K981	C103	2377 2378	(none)	
K982	K978	2376	(none)	call-on allowed
K983	C103	2378	2377	
K984	K980	2372 2375	(none)	call-on allowed
K986	K976	2369 2372 2375 2377 2378	2368	long route
	K982	2377	2378	released from red
	K984	2377 2378	(none)	